

# NEWTONTECH POWER

## POWER PACK 800

**We Build Power!**



- 1) **Genuine Quality Components.**
- 2) **Deep Sea AMF Controller.**
- 3) **Large Integrated Stainless Steel Fuel Tank.**
- 4) **Compact Design.**
- 5) **24 Months or 2000 Hours warrantee**
- 6) **Support when you need it.**
- 7) **Silent.**

[WWW.NEWTONTECHPOWER.CO.ZA](http://WWW.NEWTONTECHPOWER.CO.ZA)

602 MOOPLAATS  
PRETORIA

TEL +27 (0) 824432297  
FAX +27 (0) 866111090

[SALES@NEWTONTECHPOWER.CO.ZA](mailto:SALES@NEWTONTECHPOWER.CO.ZA)

ENGINE	CUMMINS	QSK23G3
ALTERNATOR	STAMFORD	HCI634G
ENGINE SPEED	1500	RPM
POWER	3PH 50HZ	800KVA
FUEL TANK	CAPACITY	1500L

# NEWTONTECH POWER

## POWER PACK 800

ENGINE	CUMMINS	QSX23-G3
ALTERNATOR	STAMFORD	HCI634G
ENGINE SPEED	1500	RPM
POWER	3PH 50HZ	810KVA



ENGINE	CUMMINS
FUEL	DIESEL
GOVERNER	ELECTRONIC GOVERNED
CYLINDERS	6
ASPIRATION	TURBO CHARGED INTER COOLED
DISPLACEMENT	23.1 L
COOLING SYSTEM	WATER COOLED
EMISSION	EU STAGE II
ENGINE POWER STANDBY	768 KWM @ 1500 RPM
ENGINE POWER PRIME	701 KWM @ 1500 RPM

ALTERNATOR	STAMFORD HCI634G
BASELOAD POWER	810 KVA; 50HZ; 3PH @ 40°C
CONTINUOUS POWER	800 KVA; 50HZ; 3PH @ 40°C
STAND BY POWER	880 KVA; 50HZ; 3PH @ 40°C
VOLTS	AVR CONTROLLED 380-415V-BROAD VOLTAGE
EXECUTION	BRUSHLESS
OVERLOAD (LONG TERM)	1 HOUR IN A 6 HOUR PERIOD @110% RATED

[WWW.NEWTONTECHPOWER.CO.ZA](http://WWW.NEWTONTECHPOWER.CO.ZA)

602 MOOPLAATS  
PRETORIA

TEL +27 (0) 824432297  
FAX +27 (0) 866111090

[SALES@NEWTONTECHPOWER.CO.ZA](mailto:SALES@NEWTONTECHPOWER.CO.ZA)

FUEL CONSUMPTION	
50% OF PRIME POWER	85 L/PH
75% OF PRIME POWER	121 L/PH
PRIME POWER	161 L/PH